


400

Riduttori Coassiali Versione flangiata In Line Reduction Gears Flange mounted




E ... 400

	ØA	ØB	ØC	ØC1	ØD	E	ØF1	ØF2	ØF3	ØF4	ØFc	Fc1	G	G1	H	I	I1	I2	L1	L2	L3	L4
MN		400	370 _{f7}	370 _{f7}		130	430	355	240	240	442	268	117		125	16		16	231	332	399	466
MN1		400	370 _{f7}	370 _{f7}	120 _{m6}	210	430	355	240	240	442	268	117		125	16		16	231	332	399	466
FE		400	370 _{f7}	370 _{f7}		104	430	355	240	240	442	268	117		125	16		16	231	332	399	466

400

Riduttori Ortogonali Versione flangiata Right Angle Reduction Gears Flange mounted




Solo entrata Ø65 x 105
Input only Ø65 x 105

	Lc2	Lc3	Lc4	N	O	P	Q	ØR	S	ØT	ØU	V	Y	Y1	ØZ	ØZ1	b	d	d1	d2	d3	L	t
	299	378	446	25	10	85	115	120 _{f7}	W120x3x8f DIN5480	100 _{f7}	65	30x10°	◇	220**	◇	195		16	M14		12		
	299	378	446									30x10°	◇	220**	◇	195	32	16		M24 DIN 332	12	200	127
	299	378	446		15			150	N120x5x9H DIN5480	122H7		30x10°	◇	220**	◇	195		16			12		

** Y1 = 226 per i rapporti (●) nella tabella generale di scelta - ** Y1 = 226 for those ratios (●) in the general selection table

400

Riduttori Coassiali/Ortogonalni montaggio pendolare
versione FS
In line/Right angle reduction gears shaft mounted
FS version



E ... 400

L1 = EM 1400 FS L2 = ED 2400 FS L3 = ET 3400 FS L4 = EQ 4400 FS

	ØA	ØB	ØC	ØC1	ØD	ØD1	E	ØF1	ØF2	ØF3	ØF4	ØFc	Fc1	G	H	I	L1	L2
FS		400	370 _{f7}	370 _{f7}	185 _{f7}	330	110	430	355	240	240	442	268	178	125	16	231	332

◇ Solo entrata Ø65 x 105

◇ Input only Ø65 x 105

Lc2 = EC 2400 FS

Lc3 = EC 3400 FS

Lc4 = EC 4400 FS

L3	L4	L5	Lc2	Lc3	Lc4	L1min	M	N	ØP	V	Y	Y1	ØZ	ØZ1	d	d3	Ødw
399	466	75	299	378	446	830	103	40	130 _{F7}	30x10°	◇	220**	◇	195	16	12	140 _{H7}

** Y1 = 226 per i rapporti (•) nella tabella generale di scelta - ** Y1 = 226 for those ratios (•) in the general selection table

		Motori elettrici Electric motors	Supporti in entrata Input shafts	Freni Brakes
Coassiali / In Line	MN-MR-MN1-MR1-FE			
	FS			
	PD			
Ortogonalni / Right Angle	MN-MR-MN1-MR1-FE			
	FS			
	PD			

*Le dimensioni relative all'albero in entrata sono a pag. B.8

* See page B.8 for input shaft dimensions

		Motori elettrici Electric motors								Supporti in entrata Input shafts						Freni Brakes				
		63	71	80 90	100 112	132	160 180	200	225	S45R	S46	S65	S90	S150		FL 620/12	FL 635/12	FL250 FL350 FL450	FL750	FL760 FL960
		Lt								Lt						Lt				
Coassiali / In Line	EM 1400 MN																			
	ED 2400 MN	352	354	359	360	427	458	471		462	503	501						432	445	459
	ET 3400 MN	419	421	426	427	494	525	535	564	462	503							493	506	
	EQ 4400 MN	486	488	493	494	561	592	602	633	530	571							560	573	
	EM1400 FE																			
	ED 2400 FE	352	354	359	360	427	458	471		462	503	501						432	445	459
	ET 3400 FE	419	421	426	427	494	525	535	564	462	503							493	506	
	EQ 4400 FE	486	488	493	494	561	592	602	633	530	571							560	573	
Ortogonalni / Right Angle	EM 1400 FS																			
	ED 2400 FS	352	354	359	360	427	458	471	487	462	503	501						432	445	459
	ET 3400 FS	419	421	426	427	494	525	535	564	462	503							493	506	
	EQ 4400 FS	486	488	493	494	561	592	602	633	530	571							560	573	
Ortogonalni / Right Angle	EC 2400 MN									376	65k6	105	90	69	18	M20				
	EC 3400 MN*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 3400 MN	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
	EC 4400 MN*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 4400 MN	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
	EC 3400 FE*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 3400 FE	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
	EC 4400 FE*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 4400 FE	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
Ortogonalni / Right Angle	EC 2400 FS									376	65k6	105	90	69	18	M20				
	EC 3400 FS*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 3400 FS	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
	EC 4400 FS*	246	248	253	254	321	352			280	48k6	82	70	51,5	14	M10		377		
	EC 4400 FS	240	242	247	248	315	346			280	48k6	82	70	51,5	14	M10		280		
Ortogonalni / Right Angle	PDA																			

* Y = 290 / ** Y1 = 226 per i rapporti (●) nella tabella generale di scelta - * Y = 290 / ** Y1 = 226 for those ratios (●) in the general selection table