


16S

Riduttori Coassiali
Serie PDL
In Line Reduction Gears
PDL series




PDL 16 ... S

	L ₂ = PDL 162S				L ₃ = PDL 163S				L ₄ = PDL 164S											
	ØA	ØB	ØC	ØD	ØD ₁	E	E ₁	ØF ₁	ØF ₂	ØF ₃	ØF ₄	G	H	I	K	L	L ₁	L ₂	L ₃	L ₄
MN1	770	720	665 _{h7}	250 _{m6}		350		665	510	399	355	130	30	12	550	320		625	753	
FE	770	720	665 _{h7}			165		665	510	399	355	155	30	12	550			625	753	
FS	770	720	665 _{h7}	280 _{h7}	460	315	170	665	510	399	355	305	30	12	550			625	753	

16S

Riduttori Ortogonali
Serie PDC
Right Angle Reduction Gears
PDC series















PDC 16 ... S

L _{C4} = PDC 164S																							
L ₄	L ₅	L _{1min}	L _{C3}	L _{C4}	N	P	Q	ØR	S	ØT	V	Y	Y ₁	ØZ	ØZ ₁	b	d	d _w	d ₂	t			
854				886,5							30x12°	◇		◇	56	26		M30	231				
854				886,5	45	118		280	N200x5x9H DIN 5480	202 _{H7}	30x12°	◇		◇		26							
854	205	1000		886,5	30		118			200 _{H7}	30x12°	◇		◇		26	220 _{H7-H6}						

◇ Solo entrata Ø65 x 105
Input only Ø65 x 105

16S

Forme costruttive in entrata serie PDL Input side configurations PDL series

		Motori elettrici Electric motors	Supporti in entrata Input shafts	Freni Brakes
Coassiali / In Line	MN-MR-MN1-MR1-FE			
	FS			
Ortogonalni / Right Angle	MN-MR-MN1-MR1-FE			
	FS			

*Le dimensioni relative all'albero in entrata sono a pag. B.8

* See page B.8 for input shaft dimensions

16S

Dimensioni d'ingombro Dimensions

Motori elettrici Electric motors										Supporti in entrata Input shafts						Freni Brakes					
63718090100112132160180200225										S45RS46S65S90S150						FL620/12FL635/12FL250FL350FL450FL750FL760FL960					
Lt										Lt						Lt					
Coassiali / In Line	MN1-FE	162S MN1													924,5						
		163S MN1													1065						
		164S MN1					950	980	990			917	1025	1023				954	967	981	
		162S FE													924,5						
		163S FE													1065						
		164S FE					950	980	990			917	1025	1023				954	967	981	
	FS																				
	FS	162S FS														924,5					
		163S FS														1065					
		164S FS					950	980	990			917	1025	1023				954	967	981	
Ortogonalni / Right Angle	MN1-FE																				
	FS	164S FS										376	65k6	105	90	69	18	M20			
	FS																				